
## **Features and Benefits**

Better than +/- 100 ppb from -10°C to +70°C With respect to ( Fmax + Fmin ) / 2 19.200000 MHz low noise cmos output 3.3V supply ; 6.0 mA max. +/- 5 ppm min. pull with 1.5V +/- 1.0V control


## **Typical Applications**

Mobile SATCOM Mobile Radio Harsh Environments Femto-cell

## **Mechanical Drawing**







PIN	FUNCTION
#1	Vcon VC-TCXO
	GND TCXO
#2	GND
#3	OUTPUT
#4	VDD

## **Specification**

ТСХО	Sym Condition	Condition	Value			11-24	Nete	
Specification		Condition	Min.	Тур.	Max.	Unit	Note	
Operational Frequency Range	$f_0$			19.200000		MHz		
CMOS		Logic Level High	2.97		•	V		
		Logic Level Low			0.33	V		
		Output Load Capacitance			15.0	pF		
		Duty Cycle	45	50	55	%		
		Rise and Fall Times			6.0	ns		
		Start Time			2.0	ms		
Power Supply								
Voltage	$V_{CC}$		3.130	3.300	3.470	<b>&gt;</b>		
Current Consumption					6.0	mA	At maximum supply	
Frequency versus Voltage								
	+/- 5 ppm minimum							
Pad 1: Control Voltage :			0.5	1.5	2.5	V		
Frequency Stability								
Vs. Temperature	-10°C t	o +70°C			+/- 100	ppb	With respect to (Fmax + Fmin )/2	
Vs. at 25°C	Initial Accuracy one hour after exposure to two reflows		4		+/- 2000	ppb		
Vs. +/- 5% Supply Variation	@ 25°C				+/- 50	ppb		
Vs. +/- 10 % Load Variation	@ 25°0				+/- 50	ppb		
Aging								
	After 3	0 Days of Operation						
				>	+/- 1.00	ppm	First Year Maximum	
SSB Phase Noise								
		100 Hz		-120	-115			
@ 19.2 MHz	1 KHz 10 KHz			-140	-135	dBc/Hz		
W 13.2 IVII IZ				-153	-148			
		100 KHz		-155	-150			