#### **Features and Benefits**

Tight Tolerance: ±4 ppm accuracy @25°C, ±4 ppm over -40°C to +85°C

LVCMOS Output Logic

Tight symmetry (45 to 55%) available. Operation voltage: 1.8V, 2.5V, 3.3V.

Tri-state enable/disable.

Femto second phase jitter and-152dBc/Hz at 10kHz offset.


### **Typical Applications**

Wireless Connectivity Video Distribution


### **Mechanical Drawing & Pin Connections**


**Drawing No:** 

MD200035-1









Function				
Tri-state				
GND				
Output				
VDD				

Unit in mm 1mm= 0.0394 inches

To ensure optimal oscillator performance, place a by-pass capacitor of  $0.1\mu F$  as close to the part as possible between Vdd and GND pads.

# XO2521BM

### 2.5x 2.0 mm SMD Crystal Oscillator

## **Specifications**

Specification	Conditon	3.3V		2.5V		1.8V		11
		Min.	Max.	Min.	Max.	Min.	Max.	Unit
Supply Voltage		V <sub>DD</sub> -	V <sub>DD</sub> +1	V <sub>DD</sub> -	V <sub>DD</sub> +	V <sub>DD</sub> -	V <sub>DD</sub> +1	V
Variation		10%	0%	10%	10%	10%	0%	V
Frequency Range		19	60	19	60	19	60	MHz
Supply Current	19MHz-60MHz	-	10	-	7	-	5	mA
Output Level(CMOS)	Output High	2.97	-	2.25	-	1.62	-	V
	Output Low	-	0.33	-	0.25	-	0.18	V
Transition	Rise/Fall Time	-	8	-	8	-	8	nSec
Duty Cycle		45	55	44	45	45	55	%
Start Time		-	5	-	5	-	5	mSec
Tri-State(input to pin1)	Enable	2.31	-	1.75	-	1.26	-	.,
	Disable	-	0.99	-	0.75	-	0.54	V
RMS Phase Jitter	Integrated 12KHz to 20MHz	-	1	-	1	-	1	pSec
Phase Noise @26MHz	10Hz	-90						
	100Hz	-115					dDa/U=	
	1KHz	-136					dBc/Hz	
	10KHz			-15	52			
Aging	@25°C 1st year	-	±1	-	±1	-	±1	ppm
Storage Temp. Range	-	-55°C to +125°C					°C	

Note: \*Transition times are measured between 10% and 90% of VDD with an output load of 15pF

# **Frequency Stability vs. Temperature**

	±5PPM	±10PPM	±15PPM
-10°C to +60°C	Available	Available	Available
-20°C to +70°C	Conditional	Available	Available
-40°C to +85°C	Not Available	Available	Available

Note: not all combination of options are available. Other specifications may be available upon request.